



User Manual

Wallee Payment Provider Plugin – v17.0

Table of Contents

1. Introduction.....	3
2. Features.....	3
3. Working.....	4
3.1. Odoo Backend Configuration for Wallee.....	5
3.2. Payment Processing from Website	9
3.3. Order Status	10
3.4. Wallee Multi-Website for Multi-Space Backend Configuration	11
3.5. Invoice Payment Process	14
4. Technical Requirements / Compatible With:.....	20
5. Changes Log / Release Notes	20
6. Support.....	20

1. Introduction

The Wallee payment provider extension from PIT Solutions acts as a bridge between Wallee and the Odoo Web Shop, offering a standardized solution for accepting payments through a wide range of global payment providers.

Key Characteristics include:

- **Unified Payment Gateway:** This extension centralizes payments through a single gateway, enabling transactions with numerous providers including Credit/Debit Card, PostFinance E-Finance, PostFinance Card, TWINT.
- **Comprehensive Payment Processing:** Wallee goes beyond basic payment processing by providing additional features such as reconciliation services.
- **Broad Payment Network:** It connects Odoo Shop users to a payment hub that integrates with over 50 payment gateways and processors, ensuring a broad array of payment options.
- **Efficient Integration:** Utilizing REST APIs, the connector helps reduce cart abandonment by providing customers with their preferred payment methods and lowers costs through optimized payment routing.

This extension significantly enhances the payment experience for Odoo Shop users, offering flexibility and cost-effectiveness while accommodating a wide variety of payment options.

2. Features

- **Easy to Install:** Quick and straightforward installation process.
- **Flexible:** Adapts to various business needs and payment requirements.
- **User-Friendly:** Intuitive interface and configurable settings to match individual preferences.
- **Unified Payment Gateway:** Centralized payment processing through a single gateway.

- **Multiple Payment Methods:** Supports a wide range of payment options including Credit/Debit Card, PostFinance E-Finance, PostFinance Card, TWINT.
- **Transaction Management:** Efficiently handles and maintains transaction records.
- **Customizable Notifications:** Allows for tailored system notifications.
- **Multi-Website and Multi-Space Support:** Configurable for multiple websites and spaces.

3. Working

The Wallee back-end offers flexible configuration options to tailor the payment experience:

Payment Method Management: Admins can define which payment methods are available to users, customizing the payment options as needed.

Payment Completion Process: Admins have the choice to redirect users to the payment service provider's site for transaction completion or handle payments within the shop site using an I-frame. The method of handling payments (redirection, I-frame, or both) depends on the capabilities of the payment service provider.

Enhanced Security with 3D Secure: Admins can enable 3D Secure functionality to add an extra layer of security during the checkout process. When enabled, users will be directed to the 3D Secure service of the payment method to handle their payment details securely.

Customizable Notifications: Admins can adjust notification contents for various payment statuses such as pending, completed, or canceled. Additionally, system notifications like help messages and order completion thank-you messages can be customized.

Editable Documents: Order emails, invoices, reminders, packing slips, and other related documents can be modified to fit specific formats and requirements.

These features ensure a flexible, secure, and tailored payment experience for both administrators and users.


3.1. Odoo Backend Configuration for Wallee

Screenshot 1: Payment Providers Listed in Odoo Backend

You can access the payment providers through the following menu options:

- *Invoicing > Configuration > Payment Providers*
- *Website > Configuration > eCommerce > Payment Providers*


These paths will direct you to the configuration settings for managing payment providers.



Screenshot 2: Odoo Backend Configuration of Wallee Credentials

After selecting the Wallee Payment Provider from the list, navigate to the *Credentials* tab. In this section, you can enter the credentials for your Wallee Payment Provider space.

Additionally, you'll have the option to select the payment page type. Choose between *I-Frame* and *Lightbox* options to determine your preferred method of payment processing.



The screenshot shows the 'Create Wallee Provider' form in Odoo. The form is titled 'Wallee Payment Providers' and has a 'TEST MODE' banner in the top right corner. The 'State' field is set to 'Test Mode' and is highlighted with a red box. The 'Rest API UserID', 'Rest API SpaceID', and 'Application Key' fields are also highlighted with a red box. The 'Payment Page' field is set to 'Iframe'.


To configure the Wallee Payment Provider in Odoo, you will need the following details from Wallee:

1. **Rest API UserID:** The Application User ID created in app.wallee.com.
2. **Rest API SpaceID:** The Space ID obtained from app.wallee.com.
3. **Application Key:** The Application Key generated in app.wallee.com.

After entering these details, you can set the status to '**Enabled**' for live transactions or '**Test Mode**' for testing purposes.

Additionally, you can customize the payment form and payment follow-up settings within the **Configuration** tab to tailor the payment experience to your needs.


Screenshot 3: Odoo Backend Configuration



After successful configuration, you can view the payment methods and logs related to the Wallee Payment Provider as follows:

- **Payment Methods:** Click on the 'Wallee Gateways' button to view and manage the available payment methods.
- **Logs:** Click on the 'Wallee Logging' button to access and review logs related to the Wallee payment provider.


Screenshot 4: Wallee Payment Methods



The screenshot shows the 'Wallee Payment Gateways' configuration page in a software interface. The page has a navigation bar with 'Invoicing', 'Customers', 'Vendors', 'Reporting', and 'Configuration'. Below the navigation bar, there is a search bar and a breadcrumb trail: 'Payment Providers / Wallee Payment Providers / Wallee Payment Gateways'. The main content area contains a table with the following columns: Name, Payment Meth..., Transaction Interfa..., oneClick Payme..., and Image Url. The table lists several payment methods with their respective details.

<input type="checkbox"/>	Name	Payment Meth...	Transaction Interfa...	oneClick Payme...	Image Url
<input type="checkbox"/>	Credit / Debit Card	1,457,546,097,597	ONSITE	<input type="checkbox"/>	https://app-wallee.com/en-US/s/64211/resource/web/image/payment/method/credit-debit-card.svg?strategy=snapshot&snapshot=293861
<input type="checkbox"/>	TWINT	1,457,546,097,639	OFFSITE	<input type="checkbox"/>	https://app-wallee.com/en-US/s/64211/resource/web/image/payment/method/twint.svg?strategy=snapshot&snapshot=293861
<input type="checkbox"/>	PostFinance Card	1,457,546,097,597	OFFSITE	<input type="checkbox"/>	https://app-wallee.com/en-US/s/64211/resource/web/image/payment/card-brand/postfinance-card.svg?strategy=snapshot&snapshot=293861
<input type="checkbox"/>	PostFinance Pay	1,689,233,132,073	OFFSITE	<input type="checkbox"/>	https://app-wallee.com/en-US/s/64211/resource/web/image/payment/method/pf_pay.svg?strategy=snapshot&snapshot=293861
<input type="checkbox"/>	PostFinance E-Finance	1,460,954,915,005	OFFSITE	<input type="checkbox"/>	https://app-wallee.com/en-US/s/64211/resource/web/image/payment/online-banking/postfinance-e-finance.svg?strategy=snapshot&snapsh...
<input type="checkbox"/>	PostFinance Pay	1,689,233,132,073	OFFSITE	<input type="checkbox"/>	https://app-wallee.com/en-US/s/64211/resource/web/image/payment/method/pf_pay.svg?strategy=snapshot&snapshot=293861
<input type="checkbox"/>	Bancontact	1,521,548,803,555	OFFSITE	<input type="checkbox"/>	https://app-wallee.com/en-US/s/64211/resource/web/image/payment/method/bancontact.svg?strategy=snapshot&snapshot=293861
<input type="checkbox"/>	Mastercard	1,543,209,984,299	ONSITE	<input type="checkbox"/>	https://app-wallee.com/en-US/s/64211/resource/web/image/payment/method/intelligent-credit-card.svg?strategy=snapshot&snapshot=293...
<input type="checkbox"/>	Alipay	1,457,546,097,615	OFFSITE	<input type="checkbox"/>	https://app-wallee.com/en-US/s/64211/resource/web/image/payment/method/alipay.svg?strategy=snapshot&snapshot=293861

Screenshot 5: Wallee Payment Provider Logs




The screenshot shows the 'Payment Acquirer Logging' page in the same software interface. The navigation bar and breadcrumb trail are consistent with the previous screenshot. The main content area contains a table with the following columns: Created on, Type, Description, and Origin. The table lists a series of log entries with timestamps and details.

<input type="checkbox"/>	Created on	Type	Description	Origin
<input type="checkbox"/>	08/28/2024 11:21:59		200	wallee
<input type="checkbox"/>	08/28/2024 10:38:26		200	wallee
<input type="checkbox"/>	08/28/2024 10:38:10		200	wallee
<input type="checkbox"/>	08/28/2024 10:38:10		200	wallee
<input type="checkbox"/>	08/28/2024 10:38:09		200	wallee
<input type="checkbox"/>	08/28/2024 10:38:04		200	wallee
<input type="checkbox"/>	08/28/2024 10:38:03		200	wallee
<input type="checkbox"/>	08/28/2024 10:37:18		200	wallee
<input type="checkbox"/>	08/28/2024 10:37:17		200	wallee
<input type="checkbox"/>	08/28/2024 10:36:54		442	wallee
<input type="checkbox"/>	08/28/2024 10:36:49		442	wallee
<input type="checkbox"/>	08/27/2024 16:27:23		200	wallee
<input type="checkbox"/>	08/27/2024 16:27:13		200	wallee
<input type="checkbox"/>	08/27/2024 16:27:12		200	wallee
<input type="checkbox"/>	08/27/2024 16:27:06		200	wallee

3.2. Payment Processing from Website


Screenshot 6: Multiple Payment Methods Listed in the Payment Screen

Choose your preferred payment method from those listed on the payment screen based on your currency. Then, click the **'Pay Now'** button on the Odoo eCommerce payment screen to proceed to the Wallee payment interface and complete your payment.




Screenshot 7: Wallee Payment Interface – I-Frame

On this screen, enter your card details and click the **'Confirm'** button. You will then be redirected to the payment status page on the Odoo eCommerce website.




Screenshot 8: Wallee Payment Interface - Lightbox




3.3. Order Status

Screenshot 9: Order Confirmation




Screenshot 10: Order Cancelled



3.4. Wallee Multi-Website for Multi-Space Backend Configuration


Screenshot 11: Creating new Wallee Provider

For multi-website configuration, you need to create separate Wallee payment providers for each website. To do this, use the “**Create Wallee Provider**” button to set up individual payment providers for each site.




Screenshot 12: Mapping Website to Wallee Provider

Clicking the **“Create Wallee Provider”** button will create a new Wallee Provider in Odoo with a unique name. Next, you’ll need to associate this provider with the desired website and input the credentials for the Wallee space that isn’t already configured in Odoo.




If you attempt to save the Wallee provider without associating it with a website, or if you try to map it to a website that’s already assigned, the system will prevent this action and display error messages, as shown in the screenshots below.

Screenshot 13: Message Displayed without Mapping to a Website.




Screenshot 14: Message Displayed the Website is already Mapped to a Wallee Provider.




To enable multi-website functionality, you must configure the domain names for each website.

Screenshot 15: Mapping Domain to Websites.




Screenshot 16: Mapping Domain to Websites



3.5. Invoice Payment Process


Screenshot 17: Portal User Dashboard

By clicking on the **My Account** menu, users can view documents such as invoices and sales orders associated with their account.




Screenshot 18: Portal User Account Dashboard

By clicking the **Invoices** menu, users can view all their invoices.




Screenshot 19: Invoices List

Here, users can view all their invoices. From this list, they can select an invoice to proceed with the payment.




Screenshot 20: Invoices Payment Process

Click the 'Pay Now' button to proceed with the payment.




Screenshot 21: Payment Methods Listing

Select your preferred payment method to proceed with the payment, and then click the 'Pay' button to access the Wallee provider interface.




Screenshot 22: Wallee Payment Interface

Based on the Wallee provider's payment page configuration, users will see either the Wallee IFrame or Lightbox payment interface.




Screenshot 23: Payment Success Page

Once the payment is successful, users will see the confirmation message below:




Screenshot 24: Payment Failed/Cancelled Page



Screenshot 25: Invoice Payment Process from Odoo Backend

Once you generate and confirm an invoice in the Odoo backend, a 'Preview' button will appear. Clicking this button will redirect you to the portal page, where you will find a 'Pay Now' button. Clicking the 'Pay Now' button will open the payment interface as explained earlier.



Screenshot 26: Invoice Payment Process Portal Page

Website Site eCommerce Reporting Configuration My Website + New Edit

Your Logo Home Shop Contact us +1 555-555-5556 Mitchell Admin Contact Us

This is a preview of the customer portal. -> Back to edit mode

Invoices & Bills / INV/2024/00005

\$ 1,799.00 Due in 0 days

Pay Now

Download

Salesperson

Mitchell Admin Send message

Scranton, United States +1 555-555-5555

Powered by odoo

Your logo

Your Company
250 Executive Park Blvd, Suite 3400
San Francisco CA 94134
United States

Your Company, Mitchell Admin
215 Vine St
Scranton PA 18503
United States

PROFORMA Invoice INV/2024/00005

Invoice Date: 09/02/2024 Due Date: 09/02/2024

4. Technical Requirements / Compatible With:

- Technical Requirements: Odoo Sales, Payment and Website Module.
- Compatible with ODOO version 17.0.

5. Changes Log / Release Notes

Version 1.1.1: August 2024

- Added multi-website compatibility.

Version 1.0.0: April 2023

- Initial release

6. Support

If you have questions, use our contact form at webshopextension.com or email at support@webshopextension.com.